



The RDM DMX RC1 is a palm sized RDM/DMX controller. It can monitor and control DMX units compliant with RDM. DMX addresses can be detected and set remotely. It features compact and modern design, battery powered, touch screen and SD card available for storage of chases and scenes.

Key features:

- RDM Compliant
- Monitor and control and RDM devices
- Detect and set DMX address remotely
- SD card for storage chases and scenes and firmware update
- Battery powered, 8-hours' operation
- Charged via 5V 2A Micro-USB charger
- 5 inch capacitive touchscreen

RDM DMX RC1

DMX/RDM controller

Technical Data

Power supply:	5V via charger at 100-240 V AC, 50/60 Hz
Power connection:	Micro USB
DMX512/RDM:	3-pin and 5-pin XLR in&out
Display:	5" 480x854 IPS capacitive touchscreen
Battery pack type:	Li-ion 3.7V 2000mAh 7.4Wh x 2
Battery life:	8 hrs
Control protocol:	DMX, RDM
Housing:	Colour black, Plastic cover, Steel base
Size:	170 x 113 x 48mm
N.W.:	0.6kg
Environment:	IP20

Size

